



Single Phase

**NEMA**

<b>MOTOR MODEL:</b>	RD1-RS-TF-145TC-4-B-C-2
<b>FACTORY TYPE:</b>	SLF

## NEMA Rolled Steel, TEFC

ELECTRICAL DATA		
	60 Hz	50 Hz
Horsepower	2.0	-
Speed, RPM	1740	-
Voltage	115/208-230	-
# Phase	1	-
Full Load Amps	17.3/10.4-8.65	-
Power Factor	0.92	-
Nominal Efficiency	81.5	-
3/4 Load Efficiency	-	-
Service Factor	1.15	-
KVA Code	H	-
FL Amps. @ 208 V	10.4	-
Locked Rotor Current	-	-
Start Capacitor	500	-
Start Capacitor V	165	-
Run Capacitor	80	-
Run Capacitor V	250	-
Number of Leads	7	-
Connection	-	-
Coil Resistance	-	-
Load	Efficiency %	P.F.
50%	-	-
75%	-	-
100%	-	-
FULL LOAD TEMPERATURE RISE		
FL Temp Rise °C	73.7	-
3D Image Link		
<a href="#">RD1-RS-TF-145TC-4-B-C-2</a>		

GENERAL DATA			
Frame Size	145TC		
Frame Enclosure	TEFC		
Mounting	Rigid/C-Flange		
Insulation Class	F		
Duty	Cont. / S1		
NEMA Design	L		
Frame Material	Rolled Steel		
Ingress Protection	54		
Tropicalization	-		
Cable Entry	0.88"		
Feet Removable	-		
Double Drilled	true		
Paint Color	Graphite Gray		
Paint RAL	7024		
Weight lb	53.0		
MECHANICAL DATA			
DE Bearing	6205-2RZ		
NDE Bearing	6203-2RZ		
dB No-Load	-		
Rotor Wk <sup>2</sup> , Lb-Ft <sup>2</sup>	-		
Comp Ring (wavy washer)	NDE		
TORQUE VALUES		Torque lb-ft	% FLT
Locked Rotor Torque		-	-
Pull-Up Torque		-	-
Breakdown Torque		-	-
Full Load Torque		-	100.0
SITE CONDITIONS			
Ambient Temp °C		40	
Altitude Above Sea Level m		1000	

Techtop Industries  
2815 Colonnades Court  
Peachtree Corners, GA 30071  
Tel: 678-436-5540  
E-Mail: [info@techttopind.com](mailto:info@techttopind.com)



Single Phase

**NEMA**

<b>MOTOR MODEL:</b>	RD1-RS-TF-145TC-4-B-C-2
<b>FACTORY TYPE:</b>	SLF

NEMA Rolled Steel, TEFC

Non Sinusoidal (VFD) Output 2.0HP, 1740 RPM

Torque Speed (T-n) Curve



Performance Load Values, High Voltage, 60Hz

Torque Values	Torque lb-ft	% FLT	Performance Values
Locked Rotor Torque	-	-	Start Configuration
Pull-Up Torque	-	-	Starting Current (A)
Breakdown Torque	-	-	No-Load Current (A)
Full Load	-	100.0	No-Load Power Factor

% Load	Horsepower	Current, Amps	Input power, Kilowatts	Speed, RPM	Efficiency	PF
0	-	-	-	-	-	-
25	-	-	-	-	-	-
50	-	-	-	-	-	-
75	-	-	-	-	-	-
100	-	-	-	-	-	-
125	-	-	-	-	-	-